

MA 8000 Series (MA-8750, MA-8600, MA-8300, MA-8200)-POWERED MIXERS

<CHARACTERISTICS>

- Powered Mixer (8CH, 10CH Mixer + Power Amplifier)
- 256 Step Internal Digital Effector
- 7 Band Graphic EQ(Master, Monitor)

<SPECIFICATION>

Input	Mono 6CH, Stereo 2CH,Aux,Return,Tape
Output	Speaker 3CH, Effect, Send, Rec Out, Main Line Out
MIC Input(Mono)	XLR jack
Impedance	3Kohm
Input Level	-43dBV
Line Input(Mono)	TRS jack
Impedance	10Kohm
Input Level	-52dBV
MIC Input(Stereo)	XLR jack
Impedance	3Kohm
Input Level	-62dBV
Line Input(Stereo)	TRS jack
Impedance	10Kohm
Input Level	-22dBV
Tape Input(L/R)	RCA jack
Impedance	10Kohm
Input Level	-22dBV
AUX Input(L/R)	TRS jack
Impedance	10Kohm
Input Level	-22dBV
Input Channel EQ	±15dB Maximum
High	10KHz
Middle	2.5KHz
Low	100Hz
Graphic EQ	±12dB Maximum
Frequency	63Hz, 160 Hz, 400 Hz, 1KHz, 2.5KHz, 6.3KHz, 16KHz
Internal Digital Effect	256 Step
Phantom Power	+48V
Meter	5 Point
Limit Indicator	Turns on : THD ≥0.5% (MAIN)
Normal Output Power	Stereo 280W + 280W @8ohm 0.5%THD 1KHz
	Stereo 425W + 425W @4ohm 0.5%THD 1KHz
	Bridge 850W @8ohm 0.5%THD 1KHz
	Monitor 280W @8ohm 0.5%THD 1KHz
Electric Power	AC220V 60Hz
Power Consumption	750W
Weight	18Kg
Dimension (WxHxD)	497 x 324 x 324mm